

# Day 17: More Exceptions

## Objective

Yesterday's challenge taught you to manage exceptional situations by using *try* and *catch* blocks. In today's challenge, you will practice throwing and propagating an exception. Check out the [Tutorial](#) tab for learning materials and an instructional video.

## Task

Write a *Calculator* class with a single method: *int power(int,int)*. The *power* method takes two integers, *n* and *p*, as parameters and returns the integer result of  $n^p$ . If either *n* or *p* is negative, then the method must throw an exception with the message: `n and p should be non-negative`.

**Note:** Do not use an access modifier (e.g.: `public`) in the declaration for your *Calculator* class.

## Input Format

Input from stdin is handled for you by the locked stub code in your editor. The first line contains an integer, *T*, the number of test cases. Each of the *T* subsequent lines describes a test case in 2 space-separated integers that denote *n* and *p*, respectively.

## Constraints

- No Test Case will result in overflow for correctly written code.

## Output Format

Output to stdout is handled for you by the locked stub code in your editor. There are *T* lines of output, where each line contains the result of  $n^p$  as calculated by your *Calculator* class' *power* method.

## Sample Input

```
4
3 5
2 4
-1 -2
-1 3
```

## Sample Output

```
243
16
n and p should be non-negative
n and p should be non-negative
```

## Explanation

$T = 4$

$T_0$ : 3 and 5 are positive, so *power* returns the result of  $3^5$ , which is 243.

$T_1$ : **2** and **4** are positive, so *power* returns the result of  $2^4$ , which is **16**.

$T_2$ : Both inputs (**−1** and **−2**) are negative, so *power* throws an exception and **n and p should be non-negative** is printed.

$T_3$ : One of the inputs (**−1**) is negative, so *power* throws an exception and **n and p should be non-negative** is printed.